

## HS330S

### Wireless apartment alarm with intelligent control

Stylish and compact, the HS330S alarm kit has been specifically designed for apartments. Instead of a siren, the innovative keypad functions as an internal siren, and provides more great features such as Preventative Prompts and At Home Zoning Mode.



### Pack Contents:

1 x Wireless Keypad, 2 x Wireless Motion Sensor (PIR), 2 x Wireless Door and Window Sensor, 2 x Contactless Tags, 1 x 4 colour dot stickers for Contactless Tag ID, 3 x Security Window Stickers, 8 x LR6 (AA) 1.5V Battery, 6 x LR03 (AAA) 1.5V Battery, 2 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity,

### Key Features and Benefits:

**Apartment Alarm Kits** - Honeywell Apartment Alarm Kits have been designed to install in less than 30 minutes. The innovative keypad functions as an internal siren, so there's no external siren to install. All batteries and fixings are included, so simply set up the keypad and sensors and you're ready to go.

**Peace of mind** - Sleep soundly safe in the knowledge that your family and home are protected at night with At Home Zoning Mode, which protects important entry points while still allowing you to move around the house. Should anything happen while you're away, Event and Tamper Alerts will let you know if the alarm has been triggered or tampered with. Your keypad will even alert you if you've left a window or door open when you try to arm your Honeywell home alarm.

**Easy to use** - The entire family can arm and disarm your Honeywell home alarm with ease by using the keypad and contactless tags. Simply press a button on the keypad to arm, and swipe the tag against the RFID reader on the wireless keypad to disarm..

**Easy to maintain** - With a long battery life of up to two years, you won't need to worry about your Honeywell Home Alarm after you have installed it. Conveniently located low battery indicators on each accessory will notify you when it's finally time to change the batteries, and the easy-open battery compartments makes the process as easy as 1-2-3.

**Reliability and quality** - Honeywell ActivLink®, using the 868MHz frequency, is our innovative wireless protocol which delivers greater range capability of up to 200m, extended battery life of up to 2 years, and improved connection reliability with no false triggering, all supported by our 2 year product quality guarantee.

**Flexible and expandable** - Add up to 44 accessories or devices to your system, and activate and control up to 3 separate zones to suit your lifestyle and needs. You can even link any number of Honeywell Doorbells to your Honeywell Home Alarm to function as additional internal sirens.

**Easy To Install** - Honeywell Home Alarm Kits have been designed to be easily installed, with all the accessories pre-linked and ready to go out of the box. All fixings and batteries are also included, so there's nothing more to buy, and there's even optional screw-free installation on most accessories with the included sticky pads. All this is backed up by our 2 year product guarantee.

## Specification:

<b>Wireless Keypad</b>	
Colour	White
Wall mounted	Yes
Frequency / Wireless Range*	868MHz / 125m
Audible Range (Volume)	150m (94dB)
Melodies	3
Sound	Internal Siren
Alarm Time (minutes)	1
Visual Alerts	LED Indicator
Power	Battery: 8 x LR6 (AA) 1.5V - (included)
Battery Life (Years)	1
Battery Features	Low Battery Indicator
Mains Power via Micro USB	Optional external supply USB 5V 500mA
Maximum Device Capacity	18 x Wireless Motion Sensor (PIR)/Wireless Door and Window Sensor, 8 x Contactless Tag, 5 x Wireless Remote Control Key Fob, 2 x Wireless Motion Sensor (IP54), 2 x Wireless Push Button
Security Features	3 Security Zone / Auto Reset / Open Door/Window Warning / Event Alerts /30s Entry/Exit Delay / Siren Service Mode
Keypad Features	Capacitive Touch Panel Interface / Backlit Buttons / Contactless Tag RFID Reader / Programmable 4 digit user access code / Built in doorbell feature / Compatible with Doorbell and Push Button
Security Functions	Delay Arm/Disarm/Home mode/Panic Alarm
Tamper Protection	Yes
Factory Reset	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	150 (h) x 140 (w) x 30 (d) / 326 (g)
Fixings	Brackets / Rawl Plugs / Screws

<b>Wireless Motion Sensor (PIR) ( x 2 )</b>	
Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 3 x LR03 (AAA) 1.5V - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Detection Range / Angle	12m / 105°
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	81 (h) x 61 (w) x 48 (d) / 75 (g)
Fixings	Brackets / Rawl Plugs / Screws / Sticky Pads

### Wireless Door and Window Sensor ( x 2 )

Colour	White
Wall mounted	Yes
Screwless mounting option (Sticky pads)	Yes
Frequency / Wireless Range*	868MHz / 200m
Power	Battery: 1 x CR2032 (3V) - (included)
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Test Mode	Yes
Tamper Protection	Yes
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	71 (h) x 40 (w) x 14 (d) / 28 (g)
Fixings	Screws / Sticky Pads

### Contactless Tag ( x 2 )

Colour	Black
Frequency / Wireless Range*	125kHz
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	36 (h) x 24 (w) x 5 (d) / 7 (g)

### Pack

EAN Code / Standard Pack EAN Code	5004100965875 / 5004100966322
Pack Dimensions (mm) / Weight (g)	325 (h) x 177 (w) x 212 (d) / 1500 (g)
Standard Pack Quantity	3

\* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.